



# BS 2PD

## Motion Detection Sensor



It detects movements occurring in the environment up to 12 meters away and allows you to be notified with warnings and notifications via Sensaway central management software as soon as motion is detected.

### TECHNICAL SPECIFICATIONS

Distance : 12m

Optic : Fresnel Lens

Input Power : 9 VDC to 15 VDC

Peak-to-peak fluctuation: 2 V (at 12 VDC)

Detector start-up time : 60 Second

Mounting Height : Min. 1.5m (4.1ft), Max. 3.1 m (10 ft.) İNSERT için - Min 1.5m, Max. 2.5m

Alarm Relay : < 24 V 50 mA (NC) max. 34  $\Omega$  resistive load

Tamper Relay: < 24 V 50 mA (NC)

### MOUNTING

Wall Mount

### MONITORING & MANAGEMENT SOFTWARE

Sensaway Monitoring & Management Software

### WEIGHT

106 g

### DIMENSIONS

Width : 60 mm

Height : 100 mm

Depth : 30 mm

### ALERT, WARNING & NOTIFICATION

Written and illuminated warning via LCD (\*1)

Email (with management software)

SMS and Phone Call (through SMS Module)

Voice warning via management software

Audible - Visual warning module (siren) (\*2)

Sensaway Mobile App Notification

(\*1) It works with BirSens modules.

(\*2) It works with compatible BirSens modules & Siren.