





Grant Instant Pass Permissions

Optionally, the list of people who switch is instantly notified to authorized persons via e-mail and SMS. You can track the door open/closed status. You can get access and pass reports by selecting a date range on the software.

GENERAL FEATURES

- 700% integrated into Sensaway software!
- · It sends instant notifications of logged in people.
- It reports access / exit status for the selected date range.
- It monitors the door open/closed status.
- Against the threat of sabotage, it sends alarm notifications when the device is disassembled.
- User management, migration and deletion via software
- The ability to open the door remotely via the web or mobile application within the given authorization.





TECHNICIAL SPECIFACITIONS

F18 ID/MF

DIMENSIONS		ELECTRICAL and OPERATING REQUIREMENTS			
Width : 183mm		Operating Temperature: 0°C +45°C & 20-80 % RH Humidity			
Height : 80mm		Power : 12V DC, 3A			
Depth : 42mm		NETWORK and SECURITY			
		10/100 Ethernet (RJ-45 Connector)			
WEIGHT		Password Protection			
720 g.		Protocols: RS232/485, TCP/IP, USB Host			
CAPACITY		WARNING, ALERT and NOTIFICATION			
5.000 ID Cards		Written and illuminated warning through LCD (*1)			
3.000 Fingerprint		Email (via management software)			
30.000 Log		SMS and Phone Call (with SMS Module)			
		Audible alert via management software			
MONITORING and MANAGEMEN	Γ SOFTWARE	Audible - Visual warning module (Siren) (*2)			
Sensaway Monitoring & Managemen	t Software	Sensaway Mobile App Notification			
		\checkmark			
SF 300	SC 700	F 18 uFace 800			
19-10					

2) ATe





Pass Records

Device Description	Passing Person	Verification Method	Passing Type	Passing Time
Company X, Site A, Data Center / Fingerprint Device	Kemal Yıldız	Fingerprint	Login	17.01.2019 17:04:05
Company X, Site A, Data Center / Fingerprint Device	Aslı Turgut	Fingerprint	Login	17.01.2019 17:04:00
Company X, Site A, Data Center / Fingerprint Device	Berk Karapınar	Card	Login	17.01.2019 17:03:11

BIR TECH

(*1) It works with BirSens modules.

^{*}2) It works with compatible BirSens modules & Siren

birtech.com



